

Park a call / Retrieve a parked call

1. To park a call, press the Programmable key (3) labelled "**Park1**" or "**Park2**" – the light will start flashing red, then hang up
2. To retrieve a parked call, press the Programmable key (3) labelled "**Park1**" or "**Park2**" that has a flashing light, then lift the Receiver

Optional: Retrieve a voicemail message

1. Press the Programmable key (3) labelled "**Mailbox**" showing a red light
2. Enter the password for your voicemail (Default: 1188)
3. Listen to the message, then follow the prompts to save, delete or replay message

Optional: Record a greeting

1. Press the Programmable key (3) labelled "**Mailbox**"
2. Enter the password for your voicemail (Default: 1188)
3. Choose "Mailbox Options" ("0"),
4. Press "1" to record the Night greeting or press "2" to record the "Day" greeting. After recording, press "1" to activate the recorded greeting.

Switch between day and night mode

1. Press the Programmable key (3) labelled "**Night**". Button will show red light
2. To switch back to day mode, press Programmable key (3) labelled "**Night**" again. The light will change to green


Detailed user manuals are available at <http://www.telequip.net/Services/TQMS.php>

For support, call our support team at 07 4047 7088 or email service@telequip.net

Quick Reference Guide for Advanced Phone



October 2017



- | | | | |
|---|---------------------|----|-----------------------------|
| 1 | LCD Screen | 6 | "Volume" key |
| 2 | Power Indicator LED | 7 | Keypad |
| 3 | Programmable keys | 8 | Scroll keys |
| 4 | "Mute" key | | "Ok" key to confirm actions |
| | "Headset" key | | "X" key to cancel actions |
| | "Message" key | 9 | Soft keys |
| | "Redial" key | 10 | Speaker |
| 5 | "Speakerphone" key | 11 | Hook switch |

Survival Functions

Make a call

1. Lift the Receiver
2. Dial the number you want to call
For internal calls, dial the extension number, for example "8201"
3. Press the "Ok" key (5)

Receive a call

When the phone rings,

1. Lift the Receiver or
2. Press the "Speakerphone" key (10)

Transfer a call

1. Press the "Transfer" Soft key (4)
2. Dial the extension you want to call , for example "8201"
3. Press the "Transfer" Soft key again (4)

Place a call on/off hold

1. Press the "Hold" Soft key (4) to place a call on hold
2. Press the flashing Programmable key (3) labelled "Call" to take a call off hold